



Core & Coil (71A) MH ~LT~ 175W

CORE & COIL HID 71A5390001D

The basic ballast is the open core and coil which is most often used as a component within a lighting luminaire. The core and coil also forms the nucleus of Philips Advance's five other ballast configurations.

Product data

| General Information | | Input Frequency | |
|------------------------------------|-------------------|---|---|
| ANSI Code | M90-M140 | Input Frequency | 60 Hz |
| Lamp Type | 100 MH | Input Current (Open Circuit) | 2.5/1.5/1.3/1.12 A |
| Number of Lamps | 1 piece/unit | Input Current (Starting) | 1.24/0.54/0.45/0.4 A |
| Circuit Type | HX-HPF | Input Current (Short Circuit) | 0.63-0.95/0.43-0.65/0.37-0.55/0.29-0.44 A |
| Ballast Type | Magnetic HID | Secondary Short Circuit Current | 1.35-1.7 A |
| Base Model | 71A5390 | Constant Wattage Deviation | 12% |
| Core Size | 3 X 4 (2 LW) | Ballast Factor (Nom) | 1 |
| Suitable For Outdoor Use | Yes | Power Factor (Nom) | 0.90 |
| Ignitor Catalog Number | LI533-H4 | Open Circuit Voltage | 260 V |
| Ignitor Temperature Rating | 105°C | Input Current (Nom) | 1.15/0.66/0.58/0.5 A A |
| Capacitor Value | 12 MFD | Input Power (Nom) | 129 W |
| Capacitor Catalog Number | 7C120M30RA | Rated Lamp Power | 100 W |
| Capacitor Requirements | 280V | Wiring | |
| Capacitor Temperature Rating | 105°C | Wire Striplength | 0.5 mm |
| Capacitor Diameter/Oval Dimensions | 1.65 in | Wire Length by Color | 12" |
| Capacitor Height | 2.75 in | Wire Type | Stranded |
| Automatic Restart | No | Remote Wiring Configuration Allowed | Yes |
| Operating and Electrical | | Max Ballast-Lamp Distance Remote Wiring | 20' |
| Input Voltage | 120/208/240/277 V | Recommended Fuse Value | 10/5/5/4 A |

Core & Coil (71A) MH ~LT~ 175W

Approval and Application

| | |
|-----------------------------------|------------------------------------|
| Open Circuit Voltage Test (Volts) | 240-300 V |
| Approval Marks | ULR CSA certificate RoHS Compliant |
| Temperature Marking | B/B/A/A |
| UL Recognized | Yes |
| Hipot Test (1 Minute) | 2000 V |
| Hipot Test (2 Seconds) | 2500 V |
| UL Insulation Class | H(180°C) |
| UL Temperature Code | 1029B |

Product Data

| | |
|---------------------------------|-----------------------------|
| Order product name | CORE & COIL HID 71A5390001D |
| EAN/UPC - Product | 781087017838 |
| Order code | 913700533009 |
| Numerator - Quantity Per Pack | 1 |
| Numerator - Packs per outer box | 1 |
| Material Nr. (12NC) | 913700533009 |
| Net Weight (Piece) | 2.541 kg |

Dimensional drawing



MH BAL 100W 90/140 QUAD KIT

| Product | C1 | C2 | A1 | A2 | B1 | B2 |
|-----------------------------|---------|--------|--------|--------|--------|--------|
| CORE & COIL HID 71A5390001D | 3.07 in | 1.5 in | 3.9 in | 3.5 in | 2.8 in | 2.4 in |





Core & Coil (71A) MH ~LT~ 175W

CORE & COIL HID 71A5390001D

The basic ballast is the open core and coil which is most often used as a component within a lighting luminaire. The core and coil also forms the nucleus of Philips Advance's five other ballast configurations.

Product data

| General Information | | Input Frequency | |
|------------------------------------|-------------------|---|---|
| ANSI Code | M90-M140 | Input Frequency | 60 Hz |
| Lamp Type | 100 MH | Input Current (Open Circuit) | 2.5/1.5/1.3/1.12 A |
| Number of Lamps | 1 piece/unit | Input Current (Starting) | 1.24/0.54/0.45/0.4 A |
| Circuit Type | HX-HPF | Input Current (Short Circuit) | 0.63-0.95/0.43-0.65/0.37-0.55/0.29-0.44 A |
| Ballast Type | Magnetic HID | Secondary Short Circuit Current | 1.35-1.7 A |
| Base Model | 71A5390 | Constant Wattage Deviation | 12% |
| Core Size | 3 X 4 (2 LW) | Ballast Factor (Nom) | 1 |
| Suitable For Outdoor Use | Yes | Power Factor (Nom) | 0.90 |
| Ignitor Catalog Number | LI533-H4 | Open Circuit Voltage | 260 V |
| Ignitor Temperature Rating | 105°C | Input Current (Nom) | 1.15/0.66/0.58/0.5 A A |
| Capacitor Value | 12 MFD | Input Power (Nom) | 129 W |
| Capacitor Catalog Number | 7C120M30RA | Rated Lamp Power | 100 W |
| Capacitor Requirements | 280V | Wiring | |
| Capacitor Temperature Rating | 105°C | Wire Striplength | 0.5 mm |
| Capacitor Diameter/Oval Dimensions | 1.65 in | Wire Length by Color | 12" |
| Capacitor Height | 2.75 in | Wire Type | Stranded |
| Automatic Restart | No | Remote Wiring Configuration Allowed | Yes |
| Operating and Electrical | | Max Ballast-Lamp Distance Remote Wiring | 20' |
| Input Voltage | 120/208/240/277 V | Recommended Fuse Value | 10/5/5/4 A |

Core & Coil (71A) MH ~LT~ 175W

Approval and Application

| | |
|-----------------------------------|------------------------------------|
| Open Circuit Voltage Test (Volts) | 240-300 V |
| Approval Marks | ULR CSA certificate RoHS Compliant |
| Temperature Marking | B/B/A/A |
| UL Recognized | Yes |
| Hipot Test (1 Minute) | 2000 V |
| Hipot Test (2 Seconds) | 2500 V |
| UL Insulation Class | H(180°C) |
| UL Temperature Code | 1029B |

Product Data

| | |
|---------------------------------|-----------------------------|
| Order product name | CORE & COIL HID 71A5390001D |
| EAN/UPC - Product | 781087017838 |
| Order code | 913700533009 |
| Numerator - Quantity Per Pack | 1 |
| Numerator - Packs per outer box | 1 |
| Material Nr. (12NC) | 913700533009 |
| Net Weight (Piece) | 2.541 kg |

Dimensional drawing



MH BAL 100W 90/140 QUAD KIT

| Product | C1 | C2 | A1 | A2 | B1 | B2 |
|-----------------------------|---------|--------|--------|--------|--------|--------|
| CORE & COIL HID 71A5390001D | 3.07 in | 1.5 in | 3.9 in | 3.5 in | 2.8 in | 2.4 in |

