



**Product Number:** 29590

**Order Abbreviation:** CF16EL/BR30/830

**General Description:** Dulux EL 16W compact fluorescent with R30 cover, integral 120V ballast, medium screwbase, Color Temperature 3000K, 82 CRI

**\* Full Case Required**

#### Product Information

Abbrev. With Packaging Info.	CF16ELBR30830 6/CS 1/SKU
Average Rated Life (hr)	8000
Base	Medium
Bulb	BR30
Color Rendering Index (CRI)	82
Color Temperature/CCT (K)	3000
Diameter (in)	2.000
Diameter (mm)	50.80
Family Brand Name	Dulux® EL
Initial Lumens at 25C	750
Mean Lumens at 25C	600
Maximum Overall Length - MOL (in)	5.7
Maximum Overall Length - MOL (mm)	144.7
Nominal Voltage (V)	120.00
Nominal Wattage (W)	16.00
Outside Diameter (in)	3.75
Outside Diameter (mm)	95.2



#### Footnotes

- Approximate initial lumens after 100 hours operation.
- Minimum starting temperature for DULUX EL lamps is 0° F, unless otherwise specified in product literature. .
- DULUX ELs meet CSA, FCC and UL requirements.
- Caution: DULUX EL units cannot be used on dimming circuits (unless the lamp is labeled dimmable), emergency exit fixtures or lights, electronic timers, photocells, lighted switches or any other switches that do not meet UL20 Sec. 7.6.15. In outdoor applications, use only in enclosed fixtures to avoid exposure to weather. Use only on 120V, 60 Hz circuits. Never disassemble or modify lamp. Install or remove unit from fixture by grasping plastic base. Best performance achieved when operated at 77degrees F (25 degrees C). 40 Watt lamp is designed for base down orientation only
- The life ratings of fluorescent lamps are based on 3 hr. operating cycles under specified conditions and with ballast meeting ANSI specifications. If operating cycle is increased, there will be a corresponding increase in the average hours life.
- Minimum starting temperature for DULUX EL lamps is 0 degrees F
- Rule of Thumb for Compact Fluorescent Lamps: Divide wattage of incandescent lamp by 4 to determine approximate wattage of compact fluorescent lamp that will provide similar light output.





**Product Number:** 29590

**Order Abbreviation:** CF16EL/BR30/830

**General Description:** Dulux EL 16W compact fluorescent with R30 cover, integral 120V ballast, medium screwbase, Color Temperature 3000K, 82 CRI

**\* Full Case Required**

#### Product Information

Abbrev. With Packaging Info.	CF16ELBR30830 6/CS 1/SKU
Average Rated Life (hr)	8000
Base	Medium
Bulb	BR30
Color Rendering Index (CRI)	82
Color Temperature/CCT (K)	3000
Diameter (in)	2.000
Diameter (mm)	50.80
Family Brand Name	Dulux® EL
Initial Lumens at 25C	750
Mean Lumens at 25C	600
Maximum Overall Length - MOL (in)	5.7
Maximum Overall Length - MOL (mm)	144.7
Nominal Voltage (V)	120.00
Nominal Wattage (W)	16.00
Outside Diameter (in)	3.75
Outside Diameter (mm)	95.2



#### Footnotes

- Approximate initial lumens after 100 hours operation.
- Minimum starting temperature for DULUX EL lamps is 0° F, unless otherwise specified in product literature. .
- DULUX ELs meet CSA, FCC and UL requirements.
- Caution: DULUX EL units cannot be used on dimming circuits (unless the lamp is labeled dimmable), emergency exit fixtures or lights, electronic timers, photocells, lighted switches or any other switches that do not meet UL20 Sec. 7.6.15. In outdoor applications, use only in enclosed fixtures to avoid exposure to weather. Use only on 120V, 60 Hz circuits. Never disassemble or modify lamp. Install or remove unit from fixture by grasping plastic base. Best performance achieved when operated at 77degrees F (25 degrees C). 40 Watt lamp is designed for base down orientation only
- The life ratings of fluorescent lamps are based on 3 hr. operating cycles under specified conditions and with ballast meeting ANSI specifications. If operating cycle is increased, there will be a corresponding increase in the average hours life.
- Minimum starting temperature for DULUX EL lamps is 0 degrees F
- Rule of Thumb for Compact Fluorescent Lamps: Divide wattage of incandescent lamp by 4 to determine approximate wattage of compact fluorescent lamp that will provide similar light output.

