



Catalog Number: MPRV-100-78  
Item Description: 100A 4T RT MTR DB PED  
UPC Code: 784572117570

Brand Name: Milbank  
Type: Ring Type Meter Socket  
Application: Meter Socket With Main And Load Center  
Standard: UL Listed  
Voltage Rating: Up to 240 Volts Alternating Current  
Amperage Rating: 200 Ampere Continuous  
Phase: 1 Phase  
Frequency Rating: 60 Hertz  
Number Of Cutouts: 1  
Cutout Size: 100 Ampere Main Breaker  
Cable Entry: Underground  
Terminal: Double Mechanical Line Side and Single Mechanical Load Side  
Mounting: Pedestal  
Enclosure: Type 3R, G90 Galvanized Steel with Powder Coat Finish



Additional Specifications: Number of Jaws:4 Terminal  
Hub Opening and Closing Plates:Plain Top  
Equipment Ground:Triplex Ground  
Bypass Provision:No Bypass  
Number Positions:1 Position

*Utility requirements may vary. Always consult the serving utility for their requirements prior to ordering or installing this equipment. This product must always be installed by a licensed electrician. Installation of this equipment may require local electrical inspector approval.*



Catalog Number: MPRV-100-78  
Item Description: 100A 4T RT MTR DB PED  
UPC Code: 784572117570

Brand Name: Milbank  
Type: Ring Type Meter Socket  
Application: Meter Socket With Main And Load Center  
Standard: UL Listed  
Voltage Rating: Up to 240 Volts Alternating Current  
Amperage Rating: 200 Ampere Continuous  
Phase: 1 Phase  
Frequency Rating: 60 Hertz  
Number Of Cutouts: 1  
Cutout Size: 100 Ampere Main Breaker  
Cable Entry: Underground  
Terminal: Double Mechanical Line Side and Single Mechanical Load Side  
Mounting: Pedestal  
Enclosure: Type 3R, G90 Galvanized Steel with Powder Coat Finish



Additional Specifications: Number of Jaws:4 Terminal  
Hub Opening and Closing Plates:Plain Top  
Equipment Ground:Triplex Ground  
Bypass Provision:No Bypass  
Number Positions:1 Position

*Utility requirements may vary. Always consult the serving utility for their requirements prior to ordering or installing this equipment. This product must always be installed by a licensed electrician. Installation of this equipment may require local electrical inspector approval.*