



A.



B.



C.



D.

PX50, PX100, PX300, & PX600 Series Safety Transformers



- Supply 12 volts to pool/spa lights, submersible fixtures, and outdoor garden lights
- Mounting brackets on the top and bottom

3R Beige Steel Enclosure

| | Model # | Input Voltage | Output Voltage | Watts |
|----|---------|----------------|-------------------|-------|
| A. | PX50 | 120 VAC, ½ Amp | 12 or 13 VAC | 50 |
| | PX100 | 120 VAC, 1 Amp | 12 or 13 VAC | 100 |
| | PX300 | 120 VAC, 3 Amp | 12, 13, or 14 VAC | 300 |
| B. | PX600 | 120 VAC, 6 Amp | 12, 13, or 14 VAC | 600 |

3R Stainless Steel Enclosure

| | Model # | Input Voltage | Output Voltage | Watts |
|----|---------|----------------|-------------------|-------|
| C. | PX50S | 120 VAC, ½ Amp | 12 or 13 VAC | 50 |
| | PX100S | 120 VAC, 1 Amp | 12 or 13 VAC | 100 |
| | PX300S | 120 VAC, 3 Amp | 12, 13, or 14 VAC | 300 |
| D. | PX600S | 120 VAC, 6 Amp | 12, 13, or 14 VAC | 600 |

Rating:

PX50/S, PX100/S, PX300/S

Size: 7 ¼" (18.4 cm) H x 5 ¼" (13.3 cm) W x 4 ½" (11.4 cm) D

Knockouts:

Bottom: (4) combination ½" – ¾"

Left: (2) combination ½" – ¾"

Back: (2) combination ½" – ¾"

Right: (2) combination ½" – ¾"

PX600/S

Size: 10" (25.4 cm) H x 10" (25.4 cm) W x 5" (12.7 cm) D

Knockouts:

Bottom: (2) combination ½" – ¾", (4) combination ¾" – 1"

Left: (2) combination ½" – ¾"

Back: (2) combination ½" – ¾"

Right: (2) combination ½" – ¾"



A.



B.



C.



D.

PX50, PX100, PX300, & PX600 Series Safety Transformers



- Supply 12 volts to pool/spa lights, submersible fixtures, and outdoor garden lights
- Mounting brackets on the top and bottom

3R Beige Steel Enclosure

| | Model # | Input Voltage | Output Voltage | Watts |
|----|---------|----------------|-------------------|-------|
| A. | PX50 | 120 VAC, ½ Amp | 12 or 13 VAC | 50 |
| | PX100 | 120 VAC, 1 Amp | 12 or 13 VAC | 100 |
| | PX300 | 120 VAC, 3 Amp | 12, 13, or 14 VAC | 300 |
| B. | PX600 | 120 VAC, 6 Amp | 12, 13, or 14 VAC | 600 |

3R Stainless Steel Enclosure

| | Model # | Input Voltage | Output Voltage | Watts |
|----|---------|----------------|-------------------|-------|
| C. | PX50S | 120 VAC, ½ Amp | 12 or 13 VAC | 50 |
| | PX100S | 120 VAC, 1 Amp | 12 or 13 VAC | 100 |
| | PX300S | 120 VAC, 3 Amp | 12, 13, or 14 VAC | 300 |
| D. | PX600S | 120 VAC, 6 Amp | 12, 13, or 14 VAC | 600 |

Rating:

PX50/S, PX100/S, PX300/S

Size: 7 ¼" (18.4 cm) H x 5 ¼" (13.3 cm) W x 4 ½" (11.4 cm) D

Knockouts:

Bottom: (4) combination ½" – ¾"

Left: (2) combination ½" – ¾"

Back: (2) combination ½" – ¾"

Right: (2) combination ½" – ¾"

PX600/S

Size: 10" (25.4 cm) H x 10" (25.4 cm) W x 5" (12.7 cm) D

Knockouts:

Bottom: (2) combination ½" – ¾", (4) combination ¾" – 1"

Left: (2) combination ½" – ¾"

Back: (2) combination ½" – ¾"

Right: (2) combination ½" – ¾"