

## **ELLIOTT ELECTRIC SUPPLY**

We Deliver...Lower Cost, Quality Products, & Personal Service

2310 N. Stallings Dr. 75964-0000, TX Nacogdoches Phone: 936-569-7941 Fax: 936-560-4685



## A10012SS 1/2" SS Spring Nut Abb Installation Products, Inc

| Catalog Number                                    | A10012SS  |
|---|---|
| Manufacturer                                      | Abb Installation Products, Inc                                    |
| Description                                       | Nut, Spring, Size 1/2 Inch, Stainless Steel, For Use With A and C |
|   | Series Channel and Inserts  |
| Weight per unit                                   | 0.1130 (lbs/each)   |
| Product Category                                  | Channel & Strut Fittings  |
| eatures   |   |
| Thread Size                                       | 1/2 - 13  |
| Thread Type                                       | Unified National Coarse (UNC)                                     |
| imensions and Weight                              |   |
| Height  | 0.358 in  |
| Width   | 1 220 in  |
| escriptions                                       |   |
| Also Known As                                     | Spring Nut (Strut)  |
|   | Boingie Nut   |
| Description                                       |   |
| extra long description                            |   |
| Long Description                                  | Nut, Spring, Size 1/2 Inch, Stainless Steel, For use with A and C |
| <br>  | Series Channel and Inserts  |
| Product Type                                      | Reg Spring Nut SZ 1/2IN STN STL                                   |
| Ianufacturer Information                          |   |
| Brand   | Superstrut  |
| GTIN  | 00616013296127  |
| Manufacturers Part Number                         | A100 1/2SS  |
| UPC   | 616013296127  |
| axonomies, Classifications, and Ca                | teaories  |
| Category Description                              | •   |
| Туре  |   |
| ackaging  |   |
| Carton  | 100   |
| Package   | 500   |
| Weight Per each                                   | 0.113   |
|   |   |
| ses, Certifications, and Standards<br>Application | For use with A and C series channel and inserts                   |
| принации  |   |